ACTUALIZACIÓN S'PHONE QC50

1.1 Instalar el SP Flash Tool

Descargar el software en el siguiente enlace: <u>www.storex.fr/download/fw/SP_Flash_Tool_v5.rar</u> Descomprima el archivo en su PC, debería tener una carpeta llamada "SP Flash Tool V5".

1.2 Instalar los controladores Universales ADB

Descargar los controladores de S'Phone en el siguiente enlace: <u>www.storex.fr/download/fw/UniversalAdbDriverSetup.msi</u> <u>www.storex.fr/download/fw/MT65XX USB VCOM drivers.rar</u> Instalar el controlador y seleccione "**Siguiente**" hasta el final de la instalación.

1.3 Descargar el archive de actualización

Descargue el archivo de actualización en el siguiente enlace, luego descomprimir el archivo en tu PC. Debería tener una carpeta llamada "**S'Phone_QC50_20141024**": <u>www.storex.fr/download/fw/S'Phone_QC50_20141024.rar</u>

Lanzar el software "SP Flash Tool", Solo tienes que pulsar dos veces sobre el archive "flash_tool.exe", contenido en "SP Flash Tool" carpeta.

download_scene.ini	19/07/2013 15:04
🛃 flash_tool.exe	26/12/2013 12:36
flashtool.qch	17/11/2013 14:50

2 Instalar la actualización (ROM)

Pulse "Scatter-loading" vaya el archivo MT65xx_Android_scatter_emmc.txt contenido en la carpeta "S'Phone_QC50_20141024".

No haga caso de mensaje de anuncio

	and a second		Develo	ad product		
	weicome	Pormat	Downio	au Keadback	Memorylest	
				Ð		
	Down	beol	21	top		
	Download	-Agent	C:\Users\n	nichael\Desktop\M	K\SP_Flash_Tool_v5.1352.01\MTK_AllInOne_DA	.bin 📴 Download Agen
	Scatter-lo	ading File				🗾 🔚 Scatter-loading
	Download	Only	-			
lediaTek	V Na	me Beg	in Address	End Address	ال	cation
+						
	-					
					001	
		0.8/4		luter	0%	

Seleccione el archive e pulse "Abrir".

🚱 logo.bin	23/07/2014 16:40	Fichier BIN
MBR	23/07/2014 16:40	Fichier
MT6572_Android_scatter.txt	23/07/2014 16:40	Document texte
🚱 preloader_ratech72_wet_rlk_jb3.bin	23/07/2014 16:40	Fichier BIN

Las ventanas abajo deben aparecer.

			Smart Phone	Flash Tool(Runtin	e Trace Mode)	- 🗆 💌				
File Options Window Help										
	Welcor	ne Format	Download Read	dback MemoryTest						
вм	[O Stop							
	Dowr	E Download Agent								
	Scatt	er-loading File	C: \Users \michael \Deskt	:op\S'Phone\S'Phone_DC	35G_20140724\MT6572_Android_scatter.txt	Catter-loading				
MT6572	Download Only									
M10572	•	Name	Begin Address	End Address	Location					
	✓	PRELOADER	0x00000000000000000	0x000000000018caf	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\preloader_r				
	~	MBR	0x00000000c00000	0x000000000c001ff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\MBR				
	◄	EBR1	0x000000000c80000	0x000000000c801ff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\EBR1				
	~	UBOOT	0x000000002920000	0x00000000295cabb	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724∖lk.bin				
	✓	BOOTIMG	0x000000002980000	0x000000002df57ff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\boot.img				
	~	RECOVERY	0x000000002f80000	0x0000000034757ff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\recovery.img				
	✓	SEC_RO	0x000000003580000	0x0000000035a0fff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\secro.img				
	✓	LOGO	0x00000003640000	0x00000000365b7cd	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\logo.bin				
	✓	ANDROID	0x000000004340000	0x00000001e61d527	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\system.img				
	 ✓ 	CACHE	0x000000036340000	0x000000036b3a0e7	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\cache.img				
	✓	USRDATA	0x00000004db40000	0x00000004f24a237	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\userdata.img				
-		0 B/s	0 Bytes	EMMC Hig	h Speed 0:00 USB: DA Download All(high speed	l,auto detect)				

Pulse "Download".

-	Welcor	Download	Download Read	Iback MemoryTest		
	Down	nload-Agent	C:\Users\michael\Deskt	top\MTK\SP_Flash_Tool_	v5.1352.01/MTK_AllinOne_DA.bin	Download Agent
	Scatt	ter-loading File	C:\Users\michael\Deskt	op\S'Phone\S'Phone_DC	35G_20140724\MT6572_Android_scatter.txt	Scatter-loading
	Down	nioad Only	-			
MT6572		Name	Begin Address	End Address	Location	
		PRELOADER	0x0000000000000000000000000000000000000	0x000000000018caf	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\preloader_r
	~	MBR	0x0000000000000000000000000000000000000	0x000000000c001ff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\MBR
		EBR1	0x000000000c80000	0x000000000c801ff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\EBR1
	~	UBOOT	0x000000002920000	0x00000000295cabb	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\lk.bin
e 🗌 🖜	•	BOOTIMG	0x000000002980000	0x000000002df57ff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\boot.img
	•	RECOVERY	0x000000002f80000	0x0000000034757ff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\recovery.img
		SEC_RO	0x000000003580000	0x0000000035a0fff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\secro.img
	•	LOGO	0x000000003640000	0x00000000365b7cd	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\logo.bin
	•	ANDROID	0x000000004340000	0x00000001e61d527	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\system.img
	~	CACHE	0x000000036340000	0x000000036b3a0e7	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\cache.img
		USRDATA	0x00000004db40000	0x00000004f24a237	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\userdata.img

Conecte su smartphone apagado y la batería retirada, con su PC a través de USB.

Debe comenzar el proceso de actualización.

La barra de progresión aparece en rojo.

_	Welcor	ne Format	Download	Readback	MemoryTest		
-	(Download	Stop				
	Down	load-Agent	C:\Users\midsael\	Desktop\//IT	K\SP_Flash_Tool	v5.1352.01/MTK_AllnOne_DA.bri	Download Agen
	Scatt	er-loading File	C:\Users\michael\	Desktop\S'Pł	one\S'Phone_DC	35G_20140724\MT6572_Android_scatter.txt	Scatter-loading
	Down	load Only	v				
572	~	Name	Begin Addres	s E	nd Address	Location	
	4	PRELOADER	0x000000000000	0.000	00000000018caf	Ci\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\preloader_r
	2	EBR1	0x0000000000c8	0000 0x00	00000000c801ff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\EBR1
Þ	×	BOOTIMG	0x00000000298	0000 0x00	0000002af57ff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\boot.img
	v 	SEC_RO	0x00000000358	0000 0000	000000035a0fff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\secro.img
	v	ANDROID	0x000000000434	0000 0000	000001e61d527	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\system.img
	4	USRDATA	0x00000004db4	0000 0x000	000004f24a237	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\userdata.img

Luego cambia a amarillo.

				Smart Phone	Flash Tool(Runtin	ne Trace Mode)	
le Options Wi	indow Help						
_		Welcon	ne Format	Download Read	Iback MemoryTest		
вм	-		Download	Stop			
		Down	load-Agent	C: \Users \michael \Pesk	top\MTK\SP_Flash_Tool_	v5.1352.01\MTK_AllInOne_DA.bin	Download Agent
		Scatt	er-loading File	C:\Users\michael\Deskt	op\S'Phone\S'Phone_DC	35G_20140724\MT6572_Android_scatter.txt	Scatter-loading
		Down	load Only	¥.			
MT6	572		Name	Begin Address	End Address	Location	
		1	PRELOADER	0x00000000000000000	0x000000000018caf	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_2014)724\preloader_r
			MBR	0x000000000c00000	0x000000000c001ff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_2014)724\MBR
		1	EBR1	0x000000000c80000	0x000000000c801ff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_2014)724\EBR1
	b	2	BOOTIMG	0x000000002960000	0x000000002df57ff	C\Users\michael\Desktop\S'Phone\S'Phone_DC35G_2014	1724\boot.img
		2	SEC_RO	0x000000003580000	0x0000000035a0fff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_2014	0724\secro.img
Chip Info		2	1040	Commission (Commission)	Conversion 1026 feet	En Utentumichaelt Desitep & Phonety Phone, DGB50, 2014	Welf Mego Irin
hip Name:	MT6572 500	4	ANDROID	0x0000000004340000	0x000000001e61d527	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_2014	0724\system.img
hip Version:	0x0000ca01		USPDATA	0x000000044b40000	0x0000000474x237	C\\ Icarc\michael\Decitor\SPhone\SPhone\DC35G_2014	1724) userdata imm
t Clock:	EXT 26M		Same AllA	0.0000000000000000000000000000000000000	0.0000000000000000000000000000000000000	salvara anno as a son op is Phone is Phone octa de conte	ere a substantial straig
tern RAM Type:	DRAM						
xtern RAM Size:	0x20000000						
EMMC Eluck	•					Download Flash 17%	
IF EMMC Hash		1	3.72M/s	78.89M	EMMC Hig	h Speed 0:25 PreLoader US8 VCOM Port (COM	8)

Aparecerá una ventana con un icono OK que indican que se terminó el proceso de actualización.



Desconecte el smartphone y luego encenderlo.

CONSEJO IMPORTANTE: Si el proceso de actualización no comienzan con la batería fuera del teléfono, por favor inserte la batería y reinicie el proceso de actualización. **SIEMPRE TELÉFONO APAGADO**.