MISE A JOUR S'PHONE DC35G

1.1 Installer SP Flash Tool

Téléchargez le logiciel qui vous permettra de mettre à jour votre téléphone sur le lien ci-dessous : www.storex.fr/download/fw/SP Flash Tool v5.rar

Décompressez le fichier sur votre ordinateur, vous devriez obtenir le dossier « SP Flash Tool V5 ».

1.2 Installer les pilotes ADB Universel

Téléchargez le pilote pour votre téléphone sur le lien ci-dessous : www.storex.fr/download/fw/UniversalAdbDriverSetup.msi www.storex.fr/download/fw/MT65XX USB VCOM drivers.rar Installez le pilote et sélectionnez « Suivant » jusqu'à la fin de l'installation.

1.3 Télécharger le fichier de mise à jour

Téléchargez le fichier de mise à jour sur le lien ci-dessous, puis décompressez le fichier sur votre PC. Vous devriez obtenir un dossier nommé « S'Phone_DC35G_20140724 » : www.storex.fr/download/fw/S'Phone DC35G 20140724.rar

Lancez « SP Flash Tool », il suffira d'appuyer deux fois sur le fichier « flash_tool.exe » contenu dans le dossier « SP Flash Tool ».

download_scene.i	ni 19/07/2013 15:04
😹 flash_tool.exe	26/12/2013 12:36
flashtool.qch	17/11/2013 14:50

2 Installer la mise à jour (ROM)

Cliquez sur « Scatter-loading » puis Naviguer jusqu'au fichier MT65xx Android scatter emmc.txt contenu dans le dossier « S'Phone_DC35G_20140724 ».

Ignorer tout message d'avertissement



Sélectionnez le fichier ci-dessous puis appuyez sur « Ouvrir ».

🚱 logo.bin	23/07/2014 16:40	Fichier BIN
MBR	23/07/2014 16:40	Fichier
MT6572_Android_scatter.txt	23/07/2014 16:40	Document texte
🚱 preloader_ratech72_wet_rlk_jb3.bin	23/07/2014 16:40	Fichier BIN

Vous devriez obtenir la fenêtre ci-dessous.

8		Smart Phone	Flash Tool(Runtim	ne Trace Mode)	- 🗆 🗙
File Options Window Help					
Welcome	e Format	Download Rear	hack MemoryTest		
	e romae		induct Friends y rest		
вм	+				
Do	ownload	Stop			
Downlo	oad-Agent	C:\Users\michael\Desk	top\/MTK\SP_Flash_Tool_	v5.1352.01\MTK_AllInOne_DA.bin	🚞 Download Agent
	- la - da - Ele		an Siphana Siphana DC	25C 20140724/MT6E72 Android control but	Contraction data
Statter	r-toauling File	C. psers finctialer peske	op p Fhone p Fhone_be	556_201407249410572_Alialoid_scatter.txt	Scatter Hoading
Downlo	oad Only	-			
MI0572	Name	Begin Address	End Address	Location	
	PRELOADER	0x0000000000000000	0x000000000018caf	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\preloader_r
	MBR	0x000000000c00000	0x000000000c001ff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\MBR
	EBR1	0x000000000c80000	0x000000000c801ff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\EBR1
	UBOOT	0x000000002920000	0x00000000295cabb	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\lk.bin
	BOOTIMG	0x000000002980000	0x000000002df57ff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\boot.img
	RECOVERY	0x000000002f80000	0x0000000034757ff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\recovery.img
	SEC_RO	0x000000003580000	0x0000000035a0fff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\secro.img
	LOGO	0x00000003640000	0x00000000365b7cd	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\logo.bin
Image: A start of the start	ANDROID	0x000000004340000	0x000000001e61d527	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\system.img
	CACHE	0x000000036340000	0x000000036b3a0e7	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\cache.img
	USRDATA	0x00000004db40000	0x00000004f24a237	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\userdata.img
	0 B/s	0 Bytes	EMMC Hig	h Speed 0:00 USB: DA Download All(high speed	,auto detect)

Appuyez sur « Download ».

	- 1			IDBOK Memory lest		
	_	Download	Stop			
	Down	nload-Agent	C: Users (michael Desk	top\MTK\SP_Flash_Tool_	v5.1352.01\MTK_AllInOne_DA.bin	Download Agent
	Scatt	ter-loading File	C:\Users\michael\Deskt	op\S'Phone\S'Phone_DC	35G_20140724/MT6572_Android_scatter.txt	Scatter-loading
	Down	nioad Only				
MT6572		Name	Begin Address	End Address	Location	
		PRELOADER	0x000000000000000000000000000000000000	0x000000000018caf	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	24\preloader_r
10 A	•	MBR	0x000000000c00000	0x000000000c001ff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\MBR
	•	EBR1	0x000000000c80000	0x000000000c801ff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\EBR1
12 24 X	•	UBOOT	0x000000002920000	0x00000000295cabb	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	24\lk.bin
		BOOTIMG	0x000000002980000	0x000000002df57ff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	24\boot.img
_	•	RECOVERY	0x000000002f80000	0x0000000034757ff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	24\recovery.img
	•	SEC_RO	0x000000003580000	0x0000000035a0fff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\secro.img
		LOGO	0x00000003540000	0x0000000365b7cd	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	24\logo.bin
	•	ANDROID	0x000000004340000	0x00000001e61d527	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\system.img
	•	CACHE	0x000000036340000	0x000000036b3a0e7	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	24\cache.img
		USRDATA	0x00000004db40000	0x00000004f24a237	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_20140	724\userdata.img

Connectez votre téléphone éteint et batterie enlevée, via USB au PC.

Le processus de flashage commence.

Une barre de progression rouge apparaît.

Welcome Format Download Readback MemoryTest Image: Stop Download Stop Download Stop Download Agent CiliaessimichaelDesktop/SPhone_DC356_20140774/WT6572_Android_scatter.txt Image: Download Scatter-loading File CiliaessimichaelDesktop/SPhone_SPhone_DC356_20140724/WT6572_Android_scatter.txt Image: Download Download Name Regin Address Location Image: Download Name Regin Address Location Image: Download Download Recommon Sphere CiliaessimichaelDesktop/SPhone_DC356_20140724/preloade Image: Download Recommon Sphere End Address Location Image: Download Image: Download Recommon Sphere End Address Location Image: Download Image: Download Recommon Sphere CiliaessimichaelDesktop/SPhone_DC356_20140724/preloade Image: Download Image: Download Recommon Sphere Recommon Sphere Recommon Sphere Recommon Sphere Image: Download Recommon Sphere Recommon Sphere Recommon Sphere Recommon Sphere Image: Download Recommon Sphere Recommon Sphere Recommon Sphere<	ions Window Help							
Image: Stage Download -Agent: C: Users/michael/Dektop/WTN(SP_Flach_Tool_vS:1352.01/WTK_AllnOne_DA.bn. Scatter-loading File: C: Users/michael/Dektop/SPhone_ISPhone_DC356_20140724/WT6572_Android_scatter.bxt Image: Scatter-loading File: C: Users/michael/Dektop/SPhone_ISPhone_DC356_20140724/WT6572_Android_scatter.bxt Image: Scatter-loading File: C: Users/michael/Dektop/SPhone_ISPhone_DC356_20140724/WT6572_Android_scatter.bxt Image: Scatter-loading File: C: Users/michael/Dektop/SPhone_DC356_20140724/preloade Image: Scatter-loading File: C: Users/michael/Dektop/SPhone_SPhone_DC356_20140724/preloade Image: Scatter-loading File: C: Users/michael/Dektop/SPhone_SPhone_DC356_20140724/preloade <tr< th=""><th></th><th>Welcom</th><th>e Format</th><th>Download F</th><th>Readback</th><th>MemoryTest</th><th></th><th></th></tr<>		Welcom	e Format	Download F	Readback	MemoryTest		
Download-Agent Ct Users/michael/Desktop/MTR(SP_Flash_Tool_vS.1352.01/MTK_AllnOne_DA.bn Download Scatter-loading File Ct Users/michael/Desktop/SPhone_DC356_20140724/MT6572_Androd_scatter.bt Download Download Only Download Download Download Marine Begin Address End Address Location Download PRELOADER 0x00000000000000000000000000000000000		D	ownload	Stop				
Scatter-loading File: Cit/Users/michael/Desktop/SPhone_DC356_20140724/MT6572_Android_scatter.txt		Downi	oad-Agent	C:\Users\midtael\p	esktop (MT	(\SP_Flash_Tool_	vS.1352.01/MTK_AllnOne_DA.bin	Download Agen
Download Orty Image: Section Image: Section Section Image: Section Section Section Image: Section Sec		Scatte	r-loading File	C:\Users\michael\De	esktop\S'Pf	one\S'Phone_DC	35G_20140724\MT6572_Android_scatter.txt	Scatter-loading
WIT6572 Name Begin Address End Address Location PRELOADER 0x00000000000000000000000000000000000		Down	load Only	~			- 110	
Image: Section 2 Description Description <thdescription< th=""></thdescription<>	IT6572	V	Name	Begin Address	E	nd Address	Location	
Image: Second		4	PRELOADER	0.0000000000000000	000 000	0000000018caf	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_2014	0724\preloader_r
▼ EBR1 0x000000000c80000 0x00000000c801ff C:\User\michaeh.Desktop\SPhone\SPhone_DC35G_20140724\sBR1 ▼ BOOTIMG 0x000000002980000 0x0000000024f57ff C:\User\michaeh.Desktop\SPhone\SPhone_DC35G_20140724\sboot.img ▼ BOOTIMG 0x0000000002980000 0x0000000024f57ff C:\User\michaeh.Desktop\SPhone\SPhone_DC35G_20140724\sboot.img ▼ BOOTIMG 0x0000000003580000 0x000000003560001 C:\User\michaeh.Desktop\SPhone\SPhone_DC35G_20140724\sboot.img ▼ BSC 0x0000000003580000 0x000000003560001 C:\User\michaeh.Desktop\SPhone\SPhone_DC35G_20140724\sboot.img ▼ BSC 0x00000000000000000000000000000000000		2	5107		100 0000	0000005:00)11	Co. Dear/Unicioan/Destrop/CPhenel/CPhenel/CPhenel/C2010, 2014	07245 ANDE
Image: Section of the sectio		1	EBR1	0x000000000c800	000 0x00	0000000c801ff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_2014	0724\EBR1
Image: SEC_RO 0x000000003580000 0x000000003540fff ChUsers\michael\Desktop\SPhone\SPhone_DC35G_20140724\secro.im Image: SEC_RO 0x000000003580000 0x000000003540fff ChUsers\michael\Desktop\SPhone\SPhone_SPhone_DC35G_20140724\secro.im Image: SEC_RO 0x000000004340000 0x000000001e61d527 ChUsers\michael\Desktop\SPhone\SPhone_SPhone_DC35G_20140724\system.im	e =	2	BOOTIMG	0x000000002980	00x00	00000024F57ff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_2014	0724\boot.img
Image: SEC_RO 0x000000003580000 0x000000003580fff CL\Users\michael\Desktop\SPhone\SPhone\SPhone_DC35G_20140724\sector.im Image: SEC_RO 0x000000004340000 0x000000001e61d527 CL\Users\michael\Desktop\SPhone\SPhone_DC35G_20140724\system.in Image: SEC_RO 0x000000004340000 0x000000001e61d527 CL\Users\michael\Desktop\SPhone\SPhone_SPhone_DC35G_20140724\system.in		2	BECOVERY.	passing the passin	-	NAMES OF TAXABLE PARTY.	Chloren methods broating SPhanel SPhine, DCDG, 2014	1727 at come string.
Image: Constraint of the second sec		1	SEC_RO	0x000000003580	000 0.00	00000035a0fff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_2014	0724\secro.img
✓ ANDROID 0x000000004340000 0x000000001e61d527 CxUsers\michae\Desktop\SPhone\SPhone_DC35G_20140724\system.in		2	1000	MOTORIES	20 200	000000000000000000000000000000000000000	CAUservenichael/Decktor/CSPhone: DC320:2014	1124) is particular.
I subject to the second sec		<u>v</u>	ANDROID	0x000000004340	000 05000	000001e61d527	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_2014	0724\system.img
USRDATA 0x00000004db40000 0x000000424237 C4Users/michae8.Decktory/SPhone/SPhone DC355 20140724/userdata			USPDATA	D-000000004/b40	000 0-000	00000454+237	Civilisem/michael/Desktop/S/Phone/S/Phone DC35G 2014	072.6 userdata imp
		1						

Suivi d'une barre jaune.

				Smart Phone	Flash Tool(Runtin	ne Trace Mode)	
e Options W	indow Help						
_		Welco	me Format	Download Read	dback MemoryTest		
вм	_		Download	Stop			
		Down	nload-Agent	C:\Users\michael\Desk	top\MTK\SP_Flash_Tool_	v5.1352.01\MTK_AllInOne_DA.bin	Download Agent
		Scatt	ter-loading File	C: Users (michael (Deskt	top\\$'Phone\\$'Phone_DC	35G_20140724\MT6572_Android_scatter.txt	Scatter-loading
		Dow	nload Only	¥.			
MT6	572		Name	Begin Address	End Address	Location	
		1	PRELOADER	0x0000000000000000000000000000000000000	0x000000000018caf	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_2014	0724\preloader_r
		~					0724\MBR
		\checkmark	EBR1	0x000000000c80000	0x000000000c801ff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_2014	0724\EBR1
	_		280.01	(NGC0000001-2030000)	Generation (1994-abl)	Cr/Mseen michael Desktop/CPhona/S7Finne_012356_2014	D724DBLBDH
		1	BOOTIMG	0x000000002980000	0x000000002df57ff	C:\Users\michael\Desktop\S'Phone\S'Phone_DC35G_2014	0724\boot.img
_	_		RECOVERY			Collectored Destroy & There is Phone (CC250, 2014	1735 terreter mig
1			SEC_RO	0x000000003580000	0x000000035a0m	C:\Users\michael\Desktop\S Phone\S Phone_UC33G_2014	0724\secro.img
Chip Info			ANIDROID	0-000000001240000	0-000000001-614527	Cillings) michael Decitor (Sillings) Sillings) Sillings	1720 outers imm
hip Name:	MT6572_S00	2	Cache	0.0000000000000000000000000000000000000	number of the second se	Contract and the second s	1720 contraction
hip Version:	0x0000ca01		USRDATA	0x000000004db40000	0x00000004f24a237	C:\Users\michael\Desktop\S'Phone\S'Phone DC35G 2014	0724\userdata.img
xt Clock:	EXT_26M	- Contraction					
xtern RAM Type:	DRAM						
extern RAM Size:	0x20000000						
EMMC Elach	· · · · ·	-				Download Flash 17%	
gr envire hidsh		1	3.72M/s	78.89M	EMMC Hig	ph Speed 0:25 PreLoader US8 VCOM Port (COM	18)

Une fenêtre apparaît avec un cercle vert indiquant que le processus est terminé.



Déconnectez votre téléphone puis allumez-le.

NOTE IMPORTANTE : Si le processus de flashage ne démarre pas **sans la batterie**, veuillez insérez la batterie dans votre téléphone puis recommencer le processus. TOUJOURS TELEPHONE ETEINT.